

Default Configuration: 3 Blue + 1 Red

Detector	Filter	Fluorochrome
FL1	530/30	FITC, GFP, CFSE
FL2	585/40	PE, PE-Texas Red
FL3	670 LP	PerCP-Cy5.5, PE-Cy5, PE-Cy7, PI
FL4	675/25	APC, Alexa-647

3 Blue + 1 Red

Detector	Filter	Fluorochrome
FL1	530/30	FITC, GFP, CFSE
FL2	585/40	PE
FL3	610/20	PI, PE-Texas Red
FL4	675/25	APC, Alexa-647, PE-Cy5

2 Blue + 2 Red

Detector	Filter	Fluorochrome
FL1	530/30	FITC, GFP, CFSE
FL2	585/40	PE, PI, PE-Texas Red
FL3	780/60	APC-Cy™7 (and equivalents)
FL4	675/25	APC (and equivalents)

4 Blue

Detector	Filter	Fluorochrome
FL1	530/30	FITC, GFP, CFSE
FL2	585/40	PE, PI, PE-Texas Red
FL3	780/60	PE-Cy7 (and equivalents)
FL4	675/25	PerCP-Cy5.5, PE-Cy5

4 Blue

Detector	Filter	Fluorochrome
FL1	530/30	FITC, GFP, CFSE
FL2	585/40	PE
FL3	780/60	PE-Cy7 (and equivalents)
FL4	610/20	PI
	630/30	PE-Texas Red

4 Blue

Detector	Filter	Fluorochrome
FL1	530/30	FITC, GFP, CFSE
FL2	585/40	PE
FL3	675/25	PerCP-Cy5.5, PE-Cy5
FL4	610/20	PI
	630/30	PE-Texas Red